

Guide to Hanging a Light

1. Hook the light on to the grid pipe and finger-tighten the bolt. This will temporarily secure the light.
2. Loop the safety chain over the grid pipe and through the “yoke” on the lighting instrument. The yoke is the piece that connects the actual lighting instrument to the clamp. It is shaped like an upside-down U.
3. Use a wrench to tighten the bolt further. Usually only a quarter to a half turn is necessary. You don’t need to tighten it so much that you end up denting the grid pipe.
4. Find the power plug you will be connecting the instrument to. Generally this will be above your instrument. Make sure there is no power being supplied to the outlet. If you have any question about this, be sure to ask for help. Insert the lighting instrument’s plug into the grid outlet. Make sure the plug is inserted all the way.
5. Move to the lighting computer. Click on the number corresponding to the grid plug you used. It should highlight in red. Press the “home” button on the keyboard. Your lighting instrument should now be turned on. You can press the “end” key on the keyboard to turn the instrument off.

